



### ENGLISH

( )

In order to make the best use of your Tecdesk Model 6 SIM desk phone, please read this manual carefully. This phone is designed for use with a valid SIM card from your mobile network operator.

# PLEASE READ CAREFULLY

Please do not use the device in oil and chemical factories, around inflammable and explosive objects and in places where the use of wireless transmission is NOT permitted.

Please turn OFF the phone when cleaning the device. Use a slightly damp or anti-static dish cloth to clean the device. Do NOT use a chemical cleaner to clean the surface of the device.

Do not expose the device into direct sun light and heat.

Use ONLY the original power adapter and batteries supplied with the device. Using other/non-genuine power adaptors, batteries and accessories may cause harm and damage and will void your warranty.

This device requires a SIM Card to function properly.

Please note that data may be restricted by your SIM Card Network Operator. If you have any problems with this, please check with your SIM Card Network Operator.

### **1.0 PRODUCT DESIGN**



### **1.1 UNBOXING AND INSTALLATION**

The box includes the following: -

1 x Model 6 SIM Desk Phone 1 x Receiver / Handset Cord 1 x Model 6 Stand 1 x USB Power Adaptor 1 x Battery 1 x User Manual (this document, also available online)

To set up your device, follow the steps below: -

- 1. Connect the Receiver to the device.
- 2. Carefully insert the SIM card into the SIM card tray located under the device screen.
- 3. Insert the battery correctly into the device.
- 4. Attach the stand to the device.
- 5. Connect the USB-C power adaptor to the device and plug into a power source.
- 6. Switch on the device.

### 1.2 SIM CARD

For this device to function properly, please ensure your SIM card is activated and data is enabled. Contact your SIM Card Network Provider for your SIM plan details.

( )

When removing the SIM card from your device, please follow the below steps: -

1. Power OFF the device.

- 2. Remove the battery.
- 3. Remove the SIM card.

# **1.3 BATTERY**

On first use, please charge your device (with battery inserted) for 15 hours before removing the power adaptor. Once complete, you may repeat this step 3 times to get the best efficiency from your battery. Please note that charging from a flat battery to full takes between 3 to 4 hours.









# 2. FUNCTIONALITY EXPLAINED









### 2.1 HARD KEYS AND THEIR FUNCTIONALITY

#### 1. Touch Screen

You can use the touch screen to access the full functionality of the device including making calls, adding contacts, sending and receiving text messages, making notes, setting alarms and changing the settings of the device.

#### 2. Go Back

Press this key once to go back 1 step. Press it again to go back another step. Repeat the process until you reach the home screen on the device.

#### 3. Conference Call

During a call, press this key to create a conference call. Please note that these features are dependent on your SIM Card Network Provider.

#### 4. Transfer Call

During a call, press this key to transfer the call to an internal or external number / telephone. Please note that these features are dependent on your SIM Card Network Provider.

#### 5. Hold Call

During a call, press this key to place the caller on hold. From here, you can; add another caller to the original call or make a second call simultaneously while the original caller is on hold. Please note that these features are dependent on your SIM Card Network Provider.

#### 6. Mute Call

Press this key to mute an active call. Press this key again to unmute the call.

#### 7. Volume

Press this key to increase and decrease the volume.

#### 8. Loudspeaker

Press this key to open the dialler in loudspeaker mode or convert a call from the handset receiver to loudspeaker.

#### 9. Screen Navigation Keys

Use these keys to navigate through apps on the screen. Press the OK button to accept your selection.

#### 10. Go to Home Screen

Press this key to take you back to the home screen.

#### 11. End Call & Power ON / OFF

Press this key to end a call. Long press this key to power on the device. Long press this key to give you options to power off, reboot and select aeroplane mode. Aeroplane mode disables all connections including your voice and data.









#### 12. Answer Call & Open Dialler

Press once to accept an incoming call or open the dialler to access speed dial, recent calls, contacts, and dial pad.

### 13. Quick Call

Press this key to dial out quickly according to the set number.

#### 14. Camera

 $( \bullet )$ 

Front camera can be used for video calls.

# 2.2 ANDROID SCREENS AND THEIR FUNCTIONALITY

# 2.2.1 HOME SCREEN

#### Access: Home Screen

Access the following apps: Call, Contacts, All Apps, SMS, and Settings. Also view notifications at the top of the screen.



# 2.2.2 PRELOAD APPLICATIONS / APPS SCREEN

Access: Home Screen > Swipe up from the Home Screen This will show all preloaded apps on screen.








### 2.2.3 WIDGETS AND SHORTCUT SCREENS

Access Shortcut: Long press on the Home Screen

Long press on the Home Screen to access the Shortcuts (Wallpapers, Fast Dial, Recent App, Contact).

Access Widgets: Long press on the Applications

Long press the app that you would like a widget of.



### 2.2.4 TASK MANAGER SCREEN

Access: Long press the Home Key on the Device

( )

Long press the home key to open the task manager. From here you can close all apps open in the background.




# 2.2.5 CALL OPTION SCREENS

Access: Press the Call Key on the Device / Home Screen or choose the number from the Contacts and press the call icon

Via Home Screen, start dialing on the dialer or on the screen dialer and press the green phone icon to start the call. Via Contacts type the name of your contacts or select the contact, or press the red dialler icon to type a number.





# 2.2.6 CONTACT SETTINGS

#### Access: Contacts App > Three Lines

( )

When in 'All Contacts', press the three lines icon at the top left of the screen to access the call settings. Please note that some of the settings and parameters are dependent on your Mobile Network Provider.

( )

vodafe	one UK 09:36 🖪 🗴	60 × .d a
Θ	Contacts	
~	Labels	
+	Create label	
Acco		
	Phone	
6	SIM	
٠	Settings	

### 2.2.7 IMPORT / EXPORT

Access: Contacts > Press the three lines at the top left corner > Settings > Import/Export Contacts This feature allows you to import from SIM card, import from storage, export to SIM card, export to storage, and share visible contacts.

odafone UK 15:41 🗉		E2 ×
	Import/Export contacts	
	Copy contacts to	
	Export to .vcf file Share visible contacts	
	Share visible contacts	





### 2.2.8 TEXT MESSAGES

#### Access: Home Screen > Messages

In the Messages app, it only supports receiving short messages and cannot create new ones.



## 2.2.9 NOTIFICATIONS

( )

Access: Home Screen > Swipe down from top of Screen

You will receive notifications on your screen. To access these notifications simply swipe down from the top of the screen.







 $\bigcirc$ 

### 2.2.10 NOTIFICATIONS SETTINGS

Access: Home Screen > Swipe Down from top of Screen > Swipe down even further

Swiping the screen further down will give you access to connection settings, including Wi-Fi/WLAN, Bluetooth, data, do not disturb, power saving mode, and airplane mode.



## 2.2.11 WIFI

(

Access: Home Screen > Settings > Network & Internet > Wi-Fi Search for available wireless networks and connect your device to the internet.

vodato	one UK 15:39 B Wi-Fi	∎⊷-⊠ Q
	Use Wi-Fi	-•
Ŷ	RN-VFGC	۵
	Add network	87
	Wi-Fi preferences Wi-Fi doesn't turn back on automatically	

# 2.2.12 BLUETOOTH

Access: Home Screen > Settings > Connected Devices Connect headsets, earphones, and/or other Bluetooth devices to your phone.





### 2.2.13 DATA USAGE

#### Access: Home Screen > Settings > Network & Internet > Mobile Network

From here, you can turn your mobile data ON and OFF, monitor your mobile data usage and set mobile data limits.

vodat	one UK 15:40 📾	534 B
÷	Vodafone	<i>1</i> Q
	O B used	
	0.8	2.00 GB
	2.00 GB data warning 29 days left	
	Mobile data Access data using mobile network	•
	Mobile data lock	
	Mobile data lock Password	

### 2.2.14 DISPLAY SETTING

#### Access: Home Screen > Settings

From here, you can access all the general settings of the device, including brightness, wallpaper, font size, screen saver, etc.

← Display	∎ k⊾∞ <b>= = +</b> Q
C Display Brightness level 80%	4
wallpaper	
Dark theme	
Screen timeout After 1 minute of inactivity	
Font size Default	
Screen saver	

 $(\mathbf{O})$ 

( )



### 2.2.15 SCREEN LOCK

#### Access: Home Screen > Settings > Security

Set a screen lock password so that only you can access your device via a password, pin, or pattern.

vodafo	one UK 08:54 🗴	60 ° al 1
	Security	۹
	Screen lock None	
	Device admin apps No active apps	
	SIM card lock	
	Encryption & credentials Encrypted	
	Trust agents To use, first set a screen lock	

### **3.0 CONNECTIVITY**

### 3.1 WIFI HOTSPOT

Access: Home Screen > Settings > Network & Internet > Hotspot & Tethering > Wi-fi Hotspot This feature allows you to use your device as a data hotspot to allow other devices to connect to the internet. Please note that mobile data must be turned ON to allow for the Wi-Fi hotspot to work.

### **4.0 WORKING FREQUENCIES**

GSM: 900/1800MHz WCDMA: B1/B8 LTE-FDD: B1/B3/B5/B7/B8/B20 LTE-TDD: B38/B40/B41

### **5.0 SUPPORT**

If you are a business and require support with this device, please email b2bsupport@tecdesk.com





### SAFETY INSTRUCTIONS

Before using the phone, please read the safety instructions carefully.

### **Safety Warnings**

- 1. The working temperature is from 0 to 40 degree Celsius.
- 2. In each country there may be different rules in force regarding the use of mobile phones (for example, while driving, hospitals, service stations or aircraft).
- Observe the laws regarding the use of existing mobile phones at home and turn off the device when its use is prohibited or when it may cause interference or dangerous situations.
- 4. Use the device only in accordance with its intended use and only in places where a phone call is not dangerous.
- 5. Use the power adapter and battery as supplied or recommended by manufacturer. The risk of explosion may increase if an unsuitable or unauthentic adapter is used. The battery should never be opened or exposed to flames. Dispose the used batteries according to the current guidelines and regulations.
- 6. The correct operation of medical appliances may be altered by the use of mobile phones. Pacemaker manufacturers recommend that a minimum distance of 20cm between devices when the mobile phone is on. Do not carry your phone in your pocket or near your chest.

( )

#### Attention

- 1. Do not expose the phone to moisture or extreme heat (strong sunlight or direct radiation), or cold (persistent frost).
- 2. Do not drop the unit and avoid subjecting it to shock, impact or pressure.
- 3. The phone may cause interference to nearby televisions, radios and other electrical appliances.4. Do not ever spray with spray cleaners as it can penetrate through the holes and damage the appliance.





 $\bigcirc$ 

#### **Hearing Protection**



Adjust the volume to a moderate level. Continuous exposure to high volume may impair your hearing.

#### **Environmental Recycling**

- 1. Never dispose of the phone with household waste.
- 2. Ask your governing authority about suitable methods of disposal which minimize the risk to the environment. The cardboard box, the plastic contained in the packaging and the pieces in the mobile phone can be recycled in accordance with the rules in force on recycling.
- 3. Always follow the existing rules on the subject.
- 4. Violators are subject to sanctions and measures established by law.



The bin symbol and cross, located on the device means that when the equipment has reached the end of its useful life, it must be brought to collection centers, and that treatment must be separated from urban waste. To protect the environment, when you replace the batteries, remember to use public recycling bins specified for batteries.

For more information, please visit www.tecdesk.com.





June 2022